	<u> </u>		A 1	lome		Searc	
*	30	CURRORT					
PRODUCTS		SUPPORT	DQ	OWNLOAD		ABOUT KYORITSU	
PRODUCTS	🔣 🔣 Pha	se Indicator					
Multimeters							
Voltage Testers	MODEL	_8031					
Clamp Meters							
• Loggers	Phase Indicator with open phase checker						
Insulation Testers	 Phase indicator designed to check the presence of open phase and also the phase sequence by rotating disk and lamps. 						
Earth Testers	Can check a wide range of 3-phase power source from 110V to 600V.						
LOOP/PFC/PSC Testers			~			-	
RCD Testers							
Multi Function Testers			61		6		
Combi Tester					And a state		
Portable Appliance Testers					Q		
Power Meters					i i	B. B.	
 Sensors, Multi-Trans, Clamp Adaptors 		222					
Others				~~			
Accessories		CE Typ	e CE		Sta	andard Type	
Discontinued Products				СЕ Туре		Standard Type	
		Operational voltage	110~600V A			etandara Type	
		Time limit for continuous	>500V: within 5 minutes 50/60Hz IEC 61010-1 CAT.III 600V Pollution degree 2 5550V AC for 1 minute 106(L) × 75(W) × 40(D)mm 350g approx.				
		Frequency response					
		Applicable standards					
		Withstand Voltage					
		Dimensions					
		Weight					
		Cord 1.5m		n (R: red S: white T: blue)			
		Accessories	9029 (Carrying Case) Instruction manual				
						🐴 Page	

Copyright(c)2004 KYORITSU ELECTRICAL INSTRUMENTS WORKS, LTD.

Sitemap | Contact Us | Terms of Use | Privacy Poli